


FORM PTO-1390 (Modified) (REV 5-93)		U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE		ATTORNEY'S DOCKET NUMBER 026032-3873	
TRANSMITTAL LETTER TO THE UNITED STATES DESIGNATED/ELECTED OFFICE (DO/EO/US) CONCERNING A FILING UNDER 35 U.S.C. 371					
INTERNATIONAL APPLICATION NO. PCT/US00/40159		INTERNATIONAL FILING DATE June 7, 2000		U.S. APPLICATION NO. (if known, see 37 CFR 1.55) Not yet available 107009236	
				PRIORITY DATE CLAIMED June 7, 1999	
TITLE OF INVENTION TRANSCIVER WITH CLOSED LOOP CONTROL OF ANTENNA TUNING AND POWER LEVEL					
APPLICANT(S) FOR DO/EO/US David BLAKER; Matthew CARDWELL; Paul DUCKWORTH; and Brian HONECK.					
Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information:					
1.	<input checked="" type="checkbox"/>	This is a FIRST submission of items concerning a filing under 35 U.S.C. 371.			
2.	<input type="checkbox"/>	This is a SECOND or SUBSEQUENT submission of items concerning a filing under 35 U.S.C. 371.			
3.	<input checked="" type="checkbox"/>	This express request to begin national examination procedures (35 U.S.C. 371(f)) at any time rather than delay examination until the expiration of the applicable time limit set in 35 U.S.C. 371(b) and PCT Articles 22 and 39(1).			
4.	<input checked="" type="checkbox"/>	A proper Demand for International Preliminary Examination was made by the 19 th month from the earliest claimed priority date.			
5.	<input checked="" type="checkbox"/>	A copy of the International Application as filed (35 U.S.C. 371(c)(2))			
	<input type="checkbox"/>	is transmitted herewith (required only if not transmitted by the International Bureau).			
	<input type="checkbox"/>	has been transmitted by the International Bureau.			
	<input checked="" type="checkbox"/>	is not required, as the application was filed in the United States Receiving Office (RO/US)			
6.	<input type="checkbox"/>	A translation of the International Application into English (35 U.S.C. 371(c)(2)).			
7.	<input checked="" type="checkbox"/>	Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3))			
	<input type="checkbox"/>	are transmitted herewith (required only if not transmitted by the International Bureau).			
	<input type="checkbox"/>	have been transmitted by the International Bureau.			
	<input type="checkbox"/>	have not been made; however, the time limit for making such amendments has NOT expired.			
	<input checked="" type="checkbox"/>	have not been made and will not be made.			
8.	<input type="checkbox"/>	A translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)).			
9.	<input type="checkbox"/>	An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).			
10.	<input type="checkbox"/>	A translation of the annexes to the International Preliminary Examination Report under PCT Article 36 (35 U.S.C. 371(c)(5)).			
11.	<input type="checkbox"/>	Applicant claims small entity status under 37 CFR 1.27.			
Items 12. to 17. below concern other document(s) or information included:					
12.	<input type="checkbox"/>	An Information Disclosure Statement under 37 CFR 1.97 and 1.98.			
13.	<input type="checkbox"/>	An assignment document for recording. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included.			
14.	<input type="checkbox"/>	A FIRST preliminary amendment.			
	<input type="checkbox"/>	A SECOND or SUBSEQUENT preliminary amendment.			
15.	<input type="checkbox"/>	A substitute specification.			
16.	<input type="checkbox"/>	A change of power of attorney and/or address letter.			
17.	<input type="checkbox"/>	Other items or information: OTHER			

DATE 12-6-01 EXPRESS MAIL NO. EV004220965US

CERTIFICATE OF MAILING BY EXPRESS MAIL

I hereby certify that the attached documents, pursuant to 37 CFR 1.10, are being deposited as "Express Mail" this date with the United States Postal Service in an envelope addressed to the Assistant Commissioner for Patents, Washington, DC 20231.

By Chris Gonnella
Signature of person depositing Express Mail

U.S. APPLICATION NO. (If known, see 37 CFR 1.490) Not yet available 107 009236						INTERNATIONAL APPLICATION NO. PCT/US00/40159		ATTORNEY'S DOCKET NUMBER 026032-3873	
18. <input checked="" type="checkbox"/> The following fees are submitted:								CALCULATIONS	
Basic National Fee (37 CFR 1.492(a)(1)-(5): Search Report has been prepared by the EPO or JPO\$890.00									
International preliminary examination fee paid to USPTO (37 CFR 1.482)\$710.00									
No international preliminary examination fee paid to USPTO (37 CFR 1.482) but international search fee paid to USPTO (37 CFR 1.445(a)(2))\$740.00									
Neither international preliminary examination fee (37 CFR 1.482) nor International search fee (37 CFR 1.445(a)(2)) paid to USPTO\$1,040.00									
International preliminary examination fee paid to USPTO (37 CFR 1.482) and all claims satisfied provisions of PCT Article 33(2)-(4)\$100.00									
ENTER APPROPRIATE BASIC FEE AMOUNT =								\$890.00	
Surcharge of \$130.00 for furnishing the oath or declaration later than 20 Months from the earliest claimed priority date (37 CFR 1.492(e))								\$130.00	
Claims	Number Filed	Included in Basic Fee	Extra Claims		Rate				
Total Claims	21	-	20	=	1 x \$18.00	\$18.00			
Independent Claims	4	-	3	=	1 x \$84.00	\$84.00			
Multiple dependent claim(s) (if applicable)						\$280.00			
TOTAL OF ABOVE CALCULATIONS =								\$1122.00	
Reduction by 1/2 for filing by small entity, if applicable.								\$0.00	
SUBTOTAL =								\$1122.00	
Processing fee of \$130.00 for furnishing English translation later the 20 months from the earliest claimed priority date (37 CFR 1.492(f)).								+	
TOTAL NATIONAL FEE =								\$1122.00	
Fee for recording the enclosed assignment (37 CFR 1.21(h)). The assignment must be accompanied by an appropriate cover sheet (37 CFR 3.28, 3.31). \$40.00 per property +									
TOTAL FEES ENCLOSED =								\$1122.00	
						Amount to be:			
						refunded \$			
						charged \$			
<p>a. <input checked="" type="checkbox"/> A check in the amount of \$1122.00 to cover the above fees is enclosed.</p> <p>b. <input type="checkbox"/> Please charge my Deposit Account No. 06-1447 in the amount of \$1122.00 to the above fees. A duplicate copy of this sheet is enclosed.</p> <p>c. <input checked="" type="checkbox"/> The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any overpayment to Deposit Account No. 06-1447. A duplicate copy of this sheet is enclosed.</p>									
<p>NOTE: Where an appropriate time limit under 37 CFR 1.494 or 1.495 has not been met, a petition to revive (37 CFR 1.137(a) or (b)) must be filed and granted to restore the application to pending status.</p>									
<p>SEND ALL CORRESPONDENCE TO:</p> <p>Foley & Lardner Firstar Center 777 East Wisconsin Avenue Milwaukee, Wisconsin 53202-5367</p>									
						 SIGNATURE			
						NAME STEVEN C. BECKER			
						REGISTRATION NUMBER 42,308			



Atty. Dkt. No. 26032/3873

THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicant: BLAKER, et al.

Title: TRANSCEIVER WITH CLOSED
LOOP CONTROL OF ANTENNA
TUNING AND POWER LEVEL

Appl. No.: 10/009,236

Filing

Date: December 6, 2001

Examiner: Unknown

Art Unit: Unknown

<p>CERTIFICATE OF MAILING</p> <p>I hereby certify that this correspondence is being deposited with the United States Postal Service with sufficient postage as First Class Mail in an envelope addressed to: Commissioner for Patents, Washington, D.C. 20231, on the date below.</p> <p><u>Chris Escavaille</u> (Printed Name)</p> <p><u>Chris Escavaille</u> (Signature)</p> <p><u>January 15, 2002</u> (Date of Deposit)</p>

PRELIMINARY AMENDMENT

Commissioner for Patents
BOX NON-FEE AMENDMENT
Washington, D.C. 20231

Sir:

Prior to examination of the present application, Applicant respectfully requests that the application be amended as follows:

CROSS-REFERENCE TO RELATED APPLICATION

Before the first paragraph on page 1 of the application, please insert:

-- CROSS-REFERENCE TO RELATED APPLICATION

This application claims the benefit of U.S. Provisional Application No. 60/137,860, filed June 7, 1999. --


REMARKS

The Examiner is invited to contact the undersigned by telephone if it is felt that a telephone interview would advance the prosecution of the present application.

Respectfully submitted,

Date 1/15/02

By



FOLEY & LARDNER
Firstar Center
777 East Wisconsin Avenue
Milwaukee, Wisconsin 53202-5367
Telephone: (414) 297-5571
Facsimile: (414) 297-4900

Steven C. Becker
Attorney for Applicant
Registration No. 42,308

5 TRANSCIVER WITH CLOSED LOOP CONTROL OF ANTENNA TUNING AND
POWER LEVEL

BACKGROUND OF THE INVENTION

Trainable transceivers for use with electrically operated garage door mechanisms are an
10 increasingly popular home convenience. Such transceivers are typically permanently located in
a vehicle and are powered by a vehicle's battery. These trainable transceivers are capable of
learning the radio frequency, modulation scheme, and data code of an existing portable remote
RF transmitter associated with an existing receiving unit located in the vehicle owner's garage.
Thus, when a vehicle owner purchases a new car having such a trainable transceiver, the vehicle
owner may train the transceiver to the vehicle owner's existing clip-on remote RF transmitter
15 without requiring any new installation in the vehicle or home. Subsequently, the old clip-on
transmitter can be discarded or stored.

If a different home is purchased or an existing garage door opener is replaced, the
trainable transceiver may be retrained to match the frequency and code of any new garage
door opener receiver that is built into the garage door opening system or one which is
subsequently installed. The trainable transceiver can be trained to any remote RF transmitter
of the type utilized to actuate garage door opening mechanisms or other remotely controlled
devices such as house lights, access gates, and the like. It does so by learning not only the
code and code format (i.e., modulation scheme), but also the particular RF carrier frequency
25 of the signal transmitted by any such remote transmitter. After being trained, the trainable
transceiver actuates the garage door opening mechanism without the need for the existing
separate remote transmitter. Such a trainable transceiver is disclosed in U.S. Patent Number
5,442,340 which is hereby incorporated by reference.

Trainable transceivers may have several problems including: an antenna that is not
30 tuned at all frequencies, where the transmission range will vary as a function of frequency;
and transmission power fluctuations created by various environmental conditions and circuit
component manufacturing inconsistencies. Trainable transceivers are limited by the
amount of space they may occupy in a vehicle cabin, leading to small antenna types and
sizes, such as a loop antenna used in the present invention. In order to effectively use a small
35 loop antenna it must be very high Q and tuned exactly to the operating frequency. High Q

10009236-050603

can be understood as high efficiency and very narrow bandwidth. The higher the Q, the higher the output field strength will be. However due to the narrow bandwidth limitations of the present invention, slight mistuning can result in significant power reduction.

Trainable transceivers may also vary their power output, as a function of their duty cycle or on-time and with respect to other various environmental variables. It is possible to increase transmission output power and thus transmitter range under certain FCC regulations. The FCC regulations limit the transmission power of a such a transceiver with respect to their duty cycle. The higher the duty cycle, the less power that may be transmitted, as the transmission power level the FCC regulates is averaged over time. Thus, for a transmitter having a low duty cycle the transmission strength may be greater than that of a transmitter having a higher duty cycle.

A further problem present in prior transmitters is the variability of transmission range due to component manufacturing inconsistencies and environmental variables. The transmission range of a transceiver may be affected by temperature. For example, in cold temperatures the power output of a transmitter will be less than that at a warmer temperature. A transmitter should ensure consistent transmission range under all environmental conditions.

SUMMARY OF THE INVENTION

According to one aspect of the present invention, a trainable transceiver is provided that efficiently transmits and receives RF signals at various frequencies. Another aspect of the present invention is to provide a trainable transceiver capable of dynamically tuning an antenna for maximum efficiency at all frequencies of use. A further aspect of the present invention is to detect the RF voltage or power level of the transmission on the antenna and adjust it with reference to on-time characteristics or other variables. To achieve these and other advantages, and in accordance with the purpose of the invention as embodied and described herein, the trainable transceiver of the present invention includes a dynamically tunable antenna, a controller, a power level sense or detector circuit, and a signal generator.

In operation, the transceiver of the present invention receives and records an activation signal from an existing remote transmitter and transmits the previously encoded modulated radio frequency carrier signal provided by the signal generator. The controller is

coupled to antennas and has two modes of operation: a learning mode and an operating mode. In the learning mode, the controller receives the activation signal from the receiving antenna for storing data corresponding to the radio frequency, modulation scheme, and code of the activation signal. In the operating mode, the controller provides output data, which identifies the radio frequency and code of the received activation signal. Additionally, the controller further provides an antenna control signal electrically coupled to the control input of the dynamically tunable antenna in order to selectively control the resonance frequency of the dynamically tunable antenna to maximize the transmission efficiency of the antenna. The signal generator is coupled to the controller and the dynamically tunable antenna and is used for transmitting an encoded modulated radio frequency carrier signal, which corresponds to the received activation signal, from the receiving antenna.

Another aspect of the present invention is the ability to vary the transmit power of the transceiver by varying its RF voltage or output power with reference to the duty cycle of the transmission. The present invention maximizes the transmission range for the transceiver which is dependent on the accuracy of tune on an integral tunable antenna and the control of the transmit power level. United States Patent Number 5,699,054 discloses such an antenna and is incorporated by reference herein.

As discussed previously, the transceiver of the present invention is packaged into a small compartment and uses a small loop antenna. However, due to the narrow bandwidth limitations of the present invention, slight mistuning of a loop antenna can result in significant power reduction. To reduce mistuning effects on the transceiver of the present invention, a feedback circuit provides amplitude tuning information to an onboard microprocessor. The feedback circuit consists of a Schottky detector diode and bias components and, as previously discussed, is referred to as the power level sense or detector circuitry. The detector circuitry provides a DC voltage proportional to the RF voltage on the antenna. As the antenna is tuned toward resonance, the detector output voltage rises until resonance is reached and then begins to drop again past resonance. The microprocessor is programmed with algorithms that will tune the antenna exactly to peak resonance and optimum power levels. Additionally, the same detector output is used to evaluate and adjust the output power level of the antenna and the microprocessor is programmed with algorithms that will tune the antenna to its maximum allowable output power.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a fragmentary perspective view of a vehicle interior having an overhead console for housing the trainable transceiver, according to the preferred embodiment of the present invention;

FIG. 2 is a perspective view of a trainable transceiver, according to the preferred embodiment of the present invention;

FIG. 3 is a perspective view of a visor incorporating the trainable transceiver, according to the preferred embodiment of the present invention;

FIG. 4 is a perspective view of a mirror assembly incorporating the trainable transceiver, according to the preferred embodiment of the present invention;

FIG. 5 is an electrical circuit diagram in schematic form of the transceiver circuitry, according to the preferred embodiment of the present invention;

FIG. 6 is a flow diagram of the antenna tuning and power level adjustment at train time algorithm, according to the preferred embodiment of the present invention;

FIG. 7 is a flow diagram for the coarse tuning algorithm, according to the preferred embodiment of the present invention;

FIG. 8 is a flow diagram for the fine antenna tuning algorithm, according to the preferred embodiment of the present invention;

FIG. 9 is a flow diagram for the transmit power level control algorithm, according to the preferred embodiment of the present invention; and

FIGS 10-11 are graphs illustrating the power feedback with reference to the antenna boost voltage of the electrical circuitry, according to the preferred embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

The following description of the present invention is merely exemplary in nature and is in no way intended to limit the invention or its uses. Moreover, the following description, while depicting a tunable transceiver designed to operate with a garage door mechanism, is intended to adequately teach one skilled in the art to make and use the tunable transceiver with any similar type RF transmission and receiving applications.

FIGS. 1 and 2 show a trainable transceiver 10 of the present invention. Trainable transceiver 10 includes three pushbutton switches 12, 14, and 16, a light emitting diode (LED) 18, and an electrical circuit board and associated circuits that may be mounted in a housing 20. As explained in greater detail below, the switches 12, 14, and 16 may each be associated with a separate garage door or other device to be controlled. The trainable transceiver housing 20 is preferably of appropriate dimensions for mounting within a vehicle accessory such as an overhead console 22 as shown in FIG. 1. In the configuration shown in FIG. 1, the trainable transceiver 10 includes electrical conductors coupled to the vehicle's electrical system for receiving power from the vehicle's battery. The overhead console 22 includes other accessories such as map reading lamps 24 controlled by switches 26. It may also include an electronic compass and display (not shown).

The trainable transceiver 10 may alternatively be permanently incorporated in a vehicle accessory such as a visor 28 (FIG. 3) or a rearview mirror assembly 30 (FIG. 4). Although the trainable transceiver 10 has been shown as incorporated in a visor and mirror assembly and removably located in an overhead console compartment, the trainable transceiver 10 could be permanently or removably located in the vehicle's instrument panel or any other suitable location within the vehicle's interior.

FIG. 5 shows the electrical circuitry of the trainable transceiver 10 in schematic form. The electrical circuit schematic may be separated into seven primary components: power circuitry 32; user interface circuitry 34; a controller/microprocessor 36 and its associated circuitry which is used to execute the training, coarse tuning, fine tuning, and power level control software routines to be described later; a transceiver applications specific integrated circuit (ASIC) 38 and its associated circuitry; a voltage controlled oscillator (VCO) 40; antenna tuning circuitry 42; a plurality of antennas 44; and power level sense or detector circuitry 46.

The power supply circuitry 32 is conventionally coupled to the vehicle's battery (not shown) through a connector and is coupled to the various components of the present invention and is used for supplying the necessary operating power to the trainable transceiver 10.

The user interface circuitry 34 includes the switches 12, 14, and 16 that are electrically coupled to the data input terminals 48 of the microprocessor 36 through switch interface circuitry 50, including filtering capacitors and sinking transistors. The switches 12,

14, and 16 as programmed by the user may each correspond to a different device to be controlled such as different garage doors, electrically operated access gates, house lighting controls or the like, each of which may have their own unique operating RF frequency modulation scheme, and/or security code. Thus, the switches 12, 14, and 16 correspond to
5 different radio frequency channels that are generated by the trainable transceiver 10. Once the RF channel associated with one of the switches 12, 14, and 16 has been trained to an RF activation signal transmitted from a portable, remote original transmitter (not shown) associated with a device such as a garage door opener (not shown), the transceiver 10 will then transmit an RF signal having the identified characteristics of the RF activation signal. Each RF channel may be trained to a different RF signal such that a plurality of devices in addition to a garage door opener may be activated by depressing one of the corresponding switches 12, 14, and 16. Such other devices may include additional garage door openers, a building's interior or exterior lights, a home security system, or any other device capable of receiving an RF control signal.

The microprocessor 36 is further connected to the LED 18 by an output terminal which is illuminated when one of the switches 12, 14, and 16 is closed. The microprocessor 36 is programmed to provide signals to the LED 18. The LED 18 will be controlled by the microprocessor 36 to slowly flash when the circuit enters a training mode for one of the RF channels associated with the switches 12, 14, and 16. The LED 18 will rapidly flash when a
20 channel is successfully trained, and will slowly flash with a distinctive double blink to prompt the operator to reactuate the transceiver 10. The LED 18 may be a multi-color LED that changes color to indicate when a channel is successfully trained or to prompt the operator to reactuate the remote transmitter. Once trainable transceiver 10 is trained, the LED 18 lights continuously when one of the switches 12, 14, and 16 is depressed to indicate
25 to the user that the transceiver 10 is transmitting a signal.

The plurality of antennas 44 includes a receiving antenna 52 and a transmission antenna 54. The receiving antenna 52 which receives a signal from a remote original transmitter (not shown) is coupled to a mixer 55 and a filter 56, which process the received signal. The processed signal is applied to a series of cascaded differential IF amplifiers 57
30 coupled to a summing amplifier 58 to evaluate the transmission strength of the signal from the original transmitter. The output of the summing amplifier 58 is applied to a comparator

59 whose reference voltage is provided by the AGC output 92 of the microprocessor 36 via an D/A converter 94 (the AGC output 92 doubles as the reference voltage for the comparator 59 and the control signal to the AGC amplifier 108, as discussed below). If the input of the comparator 59 is greater than the AGC output 92 of the microprocessor 36, the comparator 59 will output a logical one signal. This logical one signal indicates to the microprocessor 36 that the power level of the original transmitter is acceptable to attempt to train the transceiver 10.

The transmission antenna 54 is preferably a dynamically tunable loop antenna coupled indirectly via a choke 62 to a reference voltage level and coupled to varactor diodes 64a and 64b. The varactor diodes 64 change the impedance characteristics of the transmission antenna 54 in response to a control voltage applied to the cathode of the varactor diodes 64. The control voltage is determined by the microprocessor 36 which provides a pulse width modulated (PWM) signal from PWM output 66 to the antenna tuning circuitry 42 which converts the PWM signal to a control voltage. By using an antenna that is dynamically tuned, one may program the microprocessor 36 to selectively adjust the resonance frequency of the transmission antenna 54 to maximize its transmission characteristics for each particular frequency at which an RF signal is transmitted.

Thus, the transmission antenna 54 may be dynamically tuned to maximize the efficiency at which it radiates a transmitted electromagnetic RF signal. In addition, when the transmission antenna 54 is dynamically tuned to a resonance frequency corresponding to the carrier frequency of the transmitted signal, the transmission antenna 54 can remove unwanted harmonics from the signal.

Coupled to the transmission antenna 54 for transmitting a learned RF control signal is the transceiver ASIC 38 and the VCO 40. The VCO has a control input terminal 68 coupled to an output terminal 70 of the microprocessor 36 for controlling the frequency output of the VCO 40. The VCO 40 also includes an oscillator block 72 which outputs a sinusoidal signal and an LC resonator 74.

The LC resonator 74 includes coupling capacitors 76a and 76b, inductors 78a and 78b, and varactor diodes 80a and 80b. The coupling capacitor 76a has one terminal connected to the oscillator 72 and the other terminal coupled to the inductor 78a and the anode of the varactor diode 80a. The coupling capacitor 76b has one terminal connected to

the oscillator 72 and the other terminal coupled to both the inductor 78b and the anode of the varactor diode 80b. The inductors 78 and varactor diodes 80 form a resonating LC circuit having a variable resonant frequency that is changed by varying the voltage to the cathodes of the varactor diodes 80. This voltage is varied through the control input terminal 68 and a resistor 82 from the output terminal 70 of the microprocessor 36. The microprocessor 36 controls the voltage applied to control input terminal 68.

A feedback loop may be incorporated into the control of the VCO 40 where the oscillation frequency is monitored by the microprocessor 36 which adjusts the voltage at the control input terminal 68 to generate the desired oscillation frequency (frequency synthesizer control). The feedback is provided by a prescaler 86 coupled to an input 88 on the microprocessor 36 which measures the frequency of the VCO 40 output signal.

The power level sense or detector circuitry 46 of the transceiver 10 provides frequency and amplitude tuning feedback for the transmission antenna 54. The detector 46 comprises a Schottky diode 96 and bias components, including a capacitor 98, functioning as a high pass filter or D.C. block, a resistor 100 tied to a voltage source (VCC), a resistor 102, a resistor 104, and a capacitor 106, functioning as a low pass filter. This detector circuitry 46 provides a DC voltage proportional to the RF voltage or power level on the transmission antenna 54. As the transmission antenna 54 is tuned toward resonance, the RF voltages on the antenna rise, likewise the detector circuitry 46 DC output voltage rises until resonance is reached and then begins to drop again past resonance. The microprocessor 36 is programmed with algorithms described below which tune the transmission antenna 54 via the varactor diodes 80 exactly to the peak resonance. It will be appreciated that the detector circuitry 46 may also be used to secure phase shift of the detected signal.

Two methods of tuning the transmission antenna 54 are use: (1) coarse tuning and (2) fine or "on the fly" tuning. Both types of tuning are performed each time one of the switches 12, 14, and 16 is actuated. Coarse tuning is performed prior to any modulation by sweeping the varactor diodes 64 across resonance. While sweeping the transmission antenna 54 varactor diode 64 voltages, the detector circuitry 46 output DC voltage is monitored. When the detector circuitry 46 output reaches a peak, the microprocessor 36 instantaneously measures and records the transmission antenna 54 tuning voltage. Then, through software, the transmission antenna 54 tune point is ascertained. Once coarse tuning is complete the

transceiver 10 will begin to transmit. As the transceiver 10 begins modulating, the fine tuning algorithm will operate similar to the coarse tuning algorithm. The fine tuning algorithm will step the varactor diodes 64, and ascertain the correct tuning voltage. Limits are in place to allow only a small amount of adjustment in the fine tuning mode.

5 A further important factor to control in the transceiver 10 of the present invention is the output power level control. The VCO 40 provides the signal input to an automatic gain control (AGC) amplifier 108 coupled to an output amplifier 110 (both located in the transceiver ASIC 38) which provide the excitation for the transmission antenna 54 and thus the power level of the transmitted signal. The AGC amplifier's 108 gain is controlled by an
10 analog voltage supplied by the microprocessor 36 from output 92 via a pulse width modulated digital to analog converter 94. Because FCC regulations allow different power levels base upon the duty cycle of a transmitted signal, it is advantageous for the trainable transceiver to be capable of dynamically adjusting the gain of the transmitted signal. The output level of the transceiver 10 is linked to the on-time of the original transmitter. The
15 shorter the on-time of the original transmitter, the more output power allowed by the FCC. By providing the AGC amplifier 108, the transceiver 10 can transmit at the maximum allowable power for each frequency and duty factor.

There are many other problematic factors which may affect the performance of the transceiver 10 power level and may be eliminated by varying the power level of the
20 transmission. These factors include: (1) manufacturing consistency and quality of circuit components; (2) environmental variables; and (3) other external loss variations. Not every integrated circuit (IC) is exactly the same as another, even though they may share the same model number. Performance changes over a three year manufacturing cycle for an IC can be
25 significant. Temperature will vary the performance of an IC, as no IC is devoid of some dependency on the temperature at which it is running and temperature may affect the output current of the amplifiers in the IC. External loss variation over process and temperature will vary the load the amplifiers will be driving.

The detector circuitry 46 voltage may be incorporated as transmission power feedback to significantly reduce transmission power process errors. As described above with
30 reference to the tuning of the transmission antenna 54, the detector circuitry 46 outputs a DC voltage that is directly proportional to the RF voltage or power level on the transmission

antenna 54. The RF voltage on the transmission antenna 54 is directly proportional to the radiated field strength of the transmission antenna. Accordingly, algorithms are incorporated into the transceiver 10 to vary the output of the AGC amplifier 108 and therefore the output amplifier 110 and the radiated field strength of the transmission antenna 54 in response to the detector circuitry 46 DC voltage feedback. This feedback may be used to control both the tuning of the transmission antenna 64 resonance and the transmission power of the transmission antenna 64.

The duty cycle is measured at train time, this is used to calculate the needed transmission power level. This value is stored in nonvolatile memory (NVM) in the microprocessor 36. Radiated field measurements were previously taken (during the product development of the transceiver 10) to characterize the exact relationship between detector 46 voltage and field strength. This information is loaded into the power level control algorithm and is used to calculate detector 46 target voltages based on the duty cycle of the desired signal.

In operation, when the transceiver 10 is activated, a target detector 46 voltage is recovered from the NVM and loaded into the power level control routine. Once the antenna is tuned, the power level control routine adjusts the AGC control voltage until the detector 46 voltage is equal to the target voltage. Ongoing monitoring of the detector 46 voltage ensures that the field strength remains constant. Thus, since the detector 46 output voltage is accurate, the output field strength is always kept very close to optimum output field strength over process, temperature and various load.

In a first example, where the duty cycle of an original transmitter will allow the increase in output of the transmission antenna 54, the AGC 108 will increase the voltage it applies to the output amplifier. The AGC 108 will be controlled by algorithms in the microprocessor 36 via the digital to analog converter 94 to increase the transmission antenna 54 output. The algorithms will calculate, according to FCC regulations, the maximum output power allowed and then monitor and control the output power on the transmission antenna 54 with feedback provided by the detector circuitry 46.

In a second example, where the transmission output power setpoint for the transmission antenna 54 has been affected by the problematic IC transmission factors detailed above, the transceiver 10 of the present invention may compensate. The detector circuitry 46

will provide feedback which is used by the microprocessor 36 and its associated algorithms to increase or decrease the output power of the transmission antenna 54 to the setpoint needed.

As seen from the two examples, the detector circuitry 46, in combination with the rest of the transceiver 10 circuitry, provides an accurate measure of the transmission power of the transmission antenna 54. By providing this feedback, the transceiver 10 may take advantage of FCC regulations to increase output power for original remote transmitters which have low duty cycles and compensate for other factors which might adversely affect the transmission power of the transceiver 10.

The software/algorithms described above will now be detailed with reference to FIGS 6-9. The algorithms used in the present invention include: a training algorithm which incorporates antenna tuning and power level adjustment; a coarse antenna tuning routine which roughly tunes the transmission antenna 54; a fine tuning or "on the fly" tuning routine which improves upon the transmission antenna 54 tuning of the coarse tuning routine; and a transmit power level control routine which varies the power output of the transmission antenna 54.

Referring to FIG. 6, the training routine 150 will now be described. The training routine 150 teaches the transceiver 10 of the present invention the radio frequency, modulation scheme, and data code for an original portable remote transmitter associated with an existing receiving unit. Starting at block 120, the operator initiates the training sequence at the user interface and, at the same time, the operator initiates the transmit function of the existing portable transmitter. The transceiver 10 will detect the frequency of the transmission on receiving antenna 52. Next at block 122, based on the frequency, the FCC power limit for continuous wave (CW) mode will be retrieved from the NVM. As discussed previously, the FCC limits transmission power with respect to duty cycle. Continuing to Blocks 124-134, the routine 150 will determine if the data code is for a specific existing portable transmitter and set the duty cycle. At block 124, if the transmitted information is from a Genie transmitter, the routine 150 will advance to block 126 and the duty cycle will be set at 50%. If the transmitted information is not from a Genie transmitter, the routine 150 will advance to block 128 which will determine if the transmitted data is rolling code with blank alternative code word (BACW). By definition, rolling code routines change the data being transmitted to a

receiver, thus varying the duty cycle. If the transmitted data is rolling code with BACW, the routine 150 will advance to block 130 which will set the duty cycle to approximately 30%. The longest duty cycle for rolling code with BACW has been empirically determined to be approximately 30%, thus approximately 30% is the worst case. If the transmitted information is not rolling code with BACW, block 132 will determine if the transmitted data is rolling code without BACW. If the transmitted data is rolling code without BACW, the routine will advance to block 134 which will set the duty cycle to 53%. The longest duty cycle for rolling code without BACW has been empirically determined to be 53%, thus 53% is the worst case. If the transmitted information is not rolling code without BACW the routine 150 will advance to block 136. Block 136 will then calculate the duty cycle based on the bit pattern trained.

After the duty cycle is determined, the routine 150 will advance to block 138 where the duty cycle is inverted and multiplied by the previously retrieved FCC power limit for the frequency of transmission. For example, a 50% duty cycle will enable the transceiver to transmit at twice the power level for a continuous wave transmission having the same frequency. After this power level has been determined, the program advances to block 140, where the power level is stored in NVM.

The routine 150 will then advance to a coarse antenna tuning block/routine 142 and a fine antenna tuning block/routine 144 which will be described in detail below. Upon completing the coarse 142 and fine antenna 144 tuning routines, the control parameters for the antenna tuning and power transmission calculations will be stored in NVM at block 148 for retransmission.

Referring to FIG. 7, the coarse antenna tuning routine 142 will now be described. The coarse antenna tuning routine will roughly tune the antenna 54 before any transmission of data takes place. The coarse antenna tuning is performed each time one of the switches 12, 14, and 16 of the user interface circuitry 36 is actuated to successfully train the transceiver 10 or transmit data to a remote receiver. Starting at block 152, the VCO 40 is set to generate the frequency which was learned from an existing portable transmitter. The VCO 40 will stabilize the generated frequency using the frequency synthesizer control previously described. The transceiver 10 will further be put into transmit mode and the peak tune level will be initialized to zero. The routine 142 will then advance to block 154 where a starting

transmission power level is read from NVM and is used to set the AGC 108. The transmission power level is held constant through the coarse tuning routine so that the detector circuit 46 output is only affected by the transmission antenna 54 tuning. Block 154 also sets the frequency tuning of the transmission antenna 54 to a default value such as 310
5 MHz in case of a hardware fault. This default level will ensure that the transmission antenna 54 is at least roughly tuned in the event of such a hardware fault. The routine 142 will then advance to block 156 where the upper and lower tuning limits for the PWM output 66/antenna tuning circuitry 42 are set. To reiterate, the PWM output 66 is the control output of the microprocessor 36 for tuning the transmission antenna 54. The antenna tuning
10 circuitry 42 converts the PWM output to a DC voltage which is applied to the varactors 64. Continuing to block 158, the voltage output from the antenna tuning circuitry 42 is ramped up via the change in the output of the PWM output 66 which is controlled by the microprocessor 36.

In block 160 the output of the detector circuit 46 is compared to the noise level. If the
15 output of the detector circuit 46 is greater than the noise floor, then the interrupts are disabled and sampling speed is increased in block 164. If the opposite is true the routine 142 will advance to block 162 where the frequency will be checked and then corrected, an led will flash if needed, and the interrupts will run. Both block 162 and 164 will advance to block 166 where a sample of the detector circuit 46 output will be taken. As previously mentioned, the
20 detector circuit 46 voltage output is directly related to the RF voltage or power level transmitted by the transmission antenna 54.

Block 168 determines if the sampled detector circuit 46 output is greater than the peak power sample. The peak power sample is the detector circuit 46 output sample of greatest magnitude which has been measured during this coarse tuning routine 142. If the
25 sampled detector circuit 46 output is greater than the peak power sample, this latest sampled detector circuit 46 output now becomes the peak power sample and is saved, as seen in blocks 170 and 172. If the sampled detector circuit 46 output is not greater than the peak power sample, the routine will return to block 158 and continue to ramp the antenna tuning circuitry 42 output voltage. The routine 142 will also continue to test if the latest detector
30 circuit 46 output is greater than the peak power sample until the antenna voltage is finished ramping, as seen in block 174. Block 174 verifies that the ramping of the antenna circuitry

42 output voltage is finished and the routine 142 then advances to block 176 which determines if the ramping of the antenna circuitry 42 output voltage has been ramped up and down. If the antenna circuitry 42 voltage has not been ramped in both directions, then the ramp direction will be changed at block 178 and the routine 142 will return to block 158 to execute the ramping blocks again.

Continuing to block 180, the PWM output 66/antenna circuitry 42 output voltage will be examined to see if its value is too low. As described above, the PWM output 66 signal is converted to a DC voltage value by the antenna circuitry 42 to bias the varactor diodes 64. A low antenna circuitry 42 output voltage may occur as a result of circuit failure. If the value is too low, a default PWM output 66/antenna circuitry 42 output voltage will be loaded at block 182. If the value is not too low, the routine 142 will advance to block 184 where the peak tuning point for the antenna 54 will be calculated.

In the next block 186, the detector circuit 46 output voltage is examined to see if its value is too low. Block 186 double checks the detector circuit 46 feedback and determines if there is a detector circuit 46 failure or total tuning failure. If the value is too low, a default PWM output 66/antenna circuitry 42 output voltage will be loaded at block 188.

Continuing to block 190 the PWM output 66/antenna circuitry output 42 is set and output to the varactor diodes 64 and the transmission power level or gain on the AGC 108 is set. The routine 142 then waits for the AGC 108 to ramp up and the transmission antenna 54 tuning voltages to finalize. Then transmission antenna 54 is then coarse tuned.

While the coarse tuning routine 142 is executed prior to any transmission, the fine tuning routine 144 is executed while the transceiver 10 is transmitting. The fine tuning routine 144 improves upon the tuning of the coarse tuning routine 142 to better tune the transmission antenna 54 for a particular transmission frequency. The fine tuning routine 144 uses smaller increments for the PWM output 66 and therefore has better resolution which leads to improved tuning for the transmission antenna 46. Beginning at block 200, the fine tuning routine 144 sets the antenna tuning point or PWM output 66 to a certain number of counts below the previously calculated coarse tuning counts which correspond to the peak power sample (generated by the detector circuit 46 output). A count is defined as the duty cycle factor for the PWM output 66. The tuning will stop when the routine reaches a certain number of counts above the coarse peak. At block 202, data will be transmitted in the

background on the transmission antenna 54. The detector circuit 46 output voltage will then be sampled at block 204. The following blocks 206 and 208 are similar to blocks 168 and 170 in the coarse tuning routine 142. In block 206, the sampled detector circuit 46 output voltage will be compared to a peak sample. If the sampled detector circuit 46 output is greater than the peak power sample, this latest sampled detector circuit 46 output is saved as the latest peak power sample. Continuing to blocks 210 and 212, four samples will be taken. Next at block 214 the routine 144 will check if it has reached the upper bound of counts over the coarse value. If the routine 144 has not reached the upper bound, then the routine 144 will return to block 202 and repeat the sampling blocks. If the upper bound has been reached, then the routine 144 will continue to block 216 and set the antenna tuning point or PWM output 66 to the peak value, finishing the fine tuning routine 144.

FIGS 10-11 illustrate the PWM output 66/antenna circuitry 42 output voltage and detector circuit 46 output voltage vs. time. As can be seen from the figures the antenna boost voltage or antenna circuitry 42 output voltage varies the power output of the transmission antenna 54. The detector circuit 46 output voltage is directly related to the power output of the transmission antenna 54. Referring to FIG. 11, the sweeping action of the antenna boost voltage varies the detector circuitry 46 output. The peak resonance points of the transmission antenna 54 may be determined by the peaks in the detector circuitry 46 output.

The coarse tuning 142 and fine tuning 144 routines are executed once at the beginning of each action by the vehicle operator. The following transmit power level control routine 218 is continuously executed upon the completion of the coarse 142 and fine 144 tuning routines. The transmit power level control routine 218 controls the output power of the transmission antenna 54 with reference to the duty cycle calculation and environmental variables. Beginning at block 220, the output for the PWM output 66 and its corresponding target peak power level for the specific remote transmitter model format being used is loaded from NVM and the peak power is set to zero. This stored target peak power level gives the power level control routine 218 a starting point in the feedback loop to improve the response of the feedback loop. Continuing to block 222, data is transmitted on transmission antenna 54. Next at block 224, the detector circuit 46 output is sampled. At block 226 the current sampled detector circuit 46 output is compared to a stored peak power value. If the current sampled detector circuit 46 output is greater than the peak power value, then the current

sampled detector circuit 46 output is stored as the new peak power value and the PWM output 92 counts is also stored. As previously discussed, the PWM output 92 is the microprocessor control output for changing the power of the transmission for transmission antenna 54. The PWM output 92 is coupled to the D/A converter 94 which controls the gain on the AGC 108.

If the current sampled detector circuit 46 output is less than the peak power value then the routine 218 continues to block 230 to determine if sixteen samples have been taken. If sixteen samples have not been taken, the routine 218 will return to block 222 and continue to take samples. If sixteen samples have been taken, the routine will continue to blocks 232-238 where the PWM output 92 counts will be adjusted with reference to the detector circuit 46 output sample. At block 232, the routine 218 will determine if the PWM output 92 is greater than eight counts from the previously loaded corresponding target power level. If the sample is greater than eight counts from the target power level, then the PWM output 92 will be adjusted by two counts. If the sample is not greater than eight counts from the target power level, then block 236 will determine if the PWM output 92 is greater than four counts from the target power level. If the sample is greater than four counts from the target power level, then the PWM output 92, will be adjusted by one count. If the sample is not greater than four counts from the target power level, then the PWM output 92 which controls the AGC 108 will be set. The AGC 108, as previously discussed, controls the RF voltage or transmission power of the transmission antenna 54. Finally, at block 242, a delay is incorporated to allow the AGC 108 to ramp up and reach its final value. The transmit power level routine will then execute continuously while an operator is actuating the user interface 34 of the transceiver.

It is to be understood that the invention is not limited to the exact construction illustrated and described above, but that various changes may be made if not thereby departing from the scope of the invention as defined in the following claims.

CLAIMS

1. A transmitter for transmitting a device activation signal or other data, for remotely actuating a device, the device activation signal having an RF carrier frequency and a power level, said transmitter comprising:

a controller operable in an operating mode or providing a tune level signal that identifies the RF carrier frequency of the device activation signal;

a signal generator circuit coupled to the controller for generating the device activation signal, such that the RF carrier frequency corresponding to the controller tune level signal is generated; and

a detector circuit for detecting the power level of the device activation signal, the detector circuit providing the detected power level to the controller.

2. The transmitter of Claim 1, further comprising a transmission antenna assembly coupled to the signal generator circuit for transmitting the device activation signal, transmission antenna assembly having an impedance and being tunable in response to a tuning signal such that the impedance of the transmission antenna assembly is controllable thereby controlling the power level of the transmitted device activation signal.

3. The transmitter of Claim 2, wherein the controller generates the tuning signal in response to the detected power level.

4. The transmitter of Claim 3, wherein the controller further includes an antenna tuning module operable for tuning the impedance of the transmission antenna assembly in response to the detected power level of the device activation signal.

5. The transmitter of Claim 4, wherein the antenna tuning module includes:

a coarse tuning module operable to tune the transmission antenna assembly before applying the modulation scheme such that power level of the device activation signal is controlled; and

a fine tuning module operable to tune the transmission antenna assembly over a limited tuning range while applying the modulation scheme.

6. The transmitter of Claim 5, further including a prescaler coupled from the signal generator circuit to the controller for providing a sample of the RF carrier frequency to the controller, wherein the controller adjusts the RF carrier frequency is adjusted to a desired frequency.

7. The transmitter of Claim 1, further comprising an gain circuit coupled to the signal generator circuit, for controlling the power level of the device activation signal, the gain circuit being responsive to a gain signal.

8. The transmitter of Claim 7, wherein the controller generates the gain signal in response to the detected power level.

9. The transmitter of Claim 1, further including a receiving antenna for receiving an activation signal of a remote transmitter, and

wherein the controller further includes a training routine module operable to store data corresponding to the original remote transmitter activation signal for generating the output signal such that the device activation signal generated by the signal generator circuit corresponds to the activation signal of the remote transmitter.

10. The transmitter of Claim 9, further comprising a gain circuit coupled to the signal generator circuit for controlling the power level of the device activation signal, the gain circuit being responsive to a gain signal provided by the controller;

the training routine module being further operable to store a starting point transmission power value from which a target detector voltage is determined; and

the controller further operable to generate the gain signal in response to the target detector voltage and the detected power level.

11. A transmitter system for transmitting a device activation signal that includes an RF carrier frequency, modulation scheme, and data code for remotely actuating a device, comprising:

a controller operable in an operating mode for providing an output signal that identifies the frequency and code of the device activation signal;

a signal generator circuit coupled to the controller for generating the device activation signal such that the RF carrier frequency and data code corresponding to the controller output signal are generated;

a transmission antenna assembly, being coupled to the signal generator circuit for transmitting the device activation signal, the transmitted activation signal having a power output; and

a detector circuit for detecting a power level representative of the transmitted activation signal power output, the detector circuit coupled to the controller for providing the detected power level.

12. The transmitter system of Claim 11, wherein the transmission antenna assembly is tunable in response to a tuning signal such that the impedance of the transmission antenna assembly is varied, whereby the power output of the transmitted activation signal is controllable.

13. The transmitter system of Claim 12 wherein the controller further includes an antenna tuning module activable for tuning the impedance of the transmission antenna assembly in response to the detected power level.

14. The transmitter system of Claim 12, further comprising a gain circuit coupled to the signal generator circuit, for controlling the power output of the device activation signal, said gain circuit being responsive to a gain signal.

15. The transmitter system of Claim 12, further comprising a gain circuit coupled to the signal generator circuit for controlling the power output of the device activation signal, the gain circuit being responsive to a gain signal provided by the controller; and

the controller being further operable to store a starting point transmission power value from which a target detector voltage is determined, the controller operable to generate the gain signal in response to the target detector voltage and the detected power level.

16. The transmitter system of Claim 15, further including a receiving antenna for receiving an original activation signal of an original remote transmitter associated with an original receiving unit, and

wherein the controller further includes a training routine module operable to store data corresponding to the original remote transmitter activation signal for generating the output signal, such that the controller output signal corresponds to the original activation signal.

17. The transmitter system of Claim 16, further comprising a user interface and wherein the signal generator circuit includes a voltage controlled oscillator.

18. A method of transmitting a device activation signal for remotely actuating a device, the device activation signal having an RF carrier frequency and a power level, comprising the steps of:

providing a transmission antenna assembly having a tunable impedance;

generating the RF carrier frequency;

generating an antenna assembly tuning signal for controlling the antenna assembly impedance;

transmitting the device activation signal;

detecting the activation signal power level; and

adjusting the antenna assembly tuning signal in response to the detected activation signal power level.

19. The method of Claim 18 further comprising the steps of:

storing a starting point transmission power value;

determining a target detector voltage based on the starting point transmission power value;

comparing the detected activation signal power level to the target detector voltage;
generating a power level control signal for controlling the power level of the device activation signal; and

adjusting the power level control signal such that the detected activation signal power level approximately corresponds to the target detector voltage.

20. The method of Claim 18 wherein the step of generating the RF carrier frequency further comprises the steps of:

generating a tune level signal for controlling the RF carrier frequency;
generating the RF carrier frequency in response to the tune level signal;
sensing the RF carrier frequency; and
adjusting the tune level signal in response to the sensed RF carrier frequency.

21. A transmitter for transmitting a device activation signal or other data, for remotely actuating a device, the device activation signal having an RF carrier frequency and a phase shift, said transmitter comprising:

a controller operable in an operating mode or providing a tune level signal that identifies the RF carrier frequency of the device activation signal;

a signal generator circuit coupled to the controller for generating the device activation signal, such that the RF carrier frequency corresponding to the controller tune level signal is generated; and

a detector circuit for detecting the phase shift of the device activation signal, the detector circuit providing the detected phase shift to the controller.

(19) World Intellectual Property Organization
International Bureau(43) International Publication Date
14 December 2000 (14.12.2000)

PCT

(10) International Publication Number
WO 00/75905 A1(51) International Patent Classification²: G08C 19/28,
17/02, H03I 7/02, H04B 7/005Holland, MI 49423 (US). DUCKWORTH, Paul [US/US];
224 159th Avenue, Holland, MI 49424 (US). HONECK,
Brian [US/US]; 13034 Blueberry Lane, Holland, MI 49424
(US).

(21) International Application Number: PCT/US00/40159

(22) International Filing Date: 7 June 2000 (07.06.2000)

(74) Agents: STEPHENSON, James, E. et al.; Harness,
Dickey & Pierce, P.L.C. P.O. Box 828, Bloomfield Hills,
MI 48303 (US).

(25) Filing Language: English

(81) Designated State (national): US.

(26) Publication Language: English

(30) Priority Data: 60/137,860 7 June 1999 (07.06.1999) US

(84) Designated States (regional): European patent (AT, BE,
CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC,
NL, PT, SE).(71) Applicant (for all designated States except US): JOHN-
SON CONTROLS INTERIORS TECHNOLOGY
CORP. [US/US]; 49200 Halyard Drive, Plymouth, MI
48170 (US).

Published:


— With international search report.

— Before the expiration of the time limit for amending the
claims and to be republished in the event of receipt of
amendments.

(72) Inventors; and

(75) Inventors/Applicants (for US only): BLAKER, David
[US/US]; 240 East 19th Street, Holland, MI 49423 (US).
CARDWELL, Matthew [US/US]; 5356 144th Avenue,For two-letter codes and other abbreviations, refer to the "Guid-
ance Notes on Codes and Abbreviations" appearing at the begin-
ning of each regular issue of the PCT Gazette.

(54) Title: TRANSCEIVER WITH CLOSED LOOP CONTROL OF ANTENNA TUNING AND POWER LEVEL





(57) Abstract: A trainable transceiver for learning and transmitting an activation signal that includes an RF carrier frequency modulated with a code for remotely actuating a device, such as a garage door opener. The trainable transceiver preferably includes a controller, a signal generator, and a dynamically tunable antenna having a variable impedance that may be selectively controlled in accordance with a detector circuit signal. The detector circuit provides a measurement of the transmission power and is also used to vary the applied transmission power of the transceiver in response to operating and environmental parameters.

209050-93260001



WO 00/75905 A1

1/8



2/8




FIG. 3





FIG. 4

10-009,236

10009236-050602



150




FIG. 6

10-009,236

1000236-000001




FIG. 7

On the fly" Fine Antenna Tuning




FIG. 8

Transmit Power Level Control






FIG. 9

8/8

Antenna tuning at train time



Transmit sweep and "on the fly" fine tuning



DECLARATION AND POWER OF ATTORNEY

As a below named inventor, I HEREBY DECLARE:

THAT my residence, post office address, and citizenship are as stated below next to my name;

THAT I believe I am the original, first, and sole inventor (if only one inventor is named below) or an original, first, and joint inventor (if plural inventors are named below or in an attached Declaration) of the subject matter which is claimed and for which a patent is sought on the invention entitled

TRANSCEIVER WITH CLOSED LOOP CONTROL OF ANTENNA TUNING AND POWER LEVEL

(Attorney Docket No. 026032-3873)

the specification of which (check one)

 is attached hereto.

 X was filed on December 6, 2001 as United States Application Number or PCT International Application Number 10/009236.

THAT I do not know and do not believe that the same invention was ever known or used by others in the United States of America, or was patented or described in any printed publication in any country, before I (we) invented it;

THAT I do not know and do not believe that the same invention was patented or described in any printed publication in any country, or in public use or on sale in the United States of America, for more than one year prior to the filing date of this United States application;

THAT I do not know and do not believe that the same invention was first patented or made the subject of an inventor's certificate that issued in any country foreign to the United States of America before the filing date of this United States application if the foreign application was filed by me (us), or by my (our) legal representatives or assigns, more than twelve months (six months for design patents) prior to the filing date of this United States application;

THAT I have reviewed and understand the contents of the above-identified specification, including the claim(s), as amended by any amendment specifically referred to above;

THAT I believe that the above-identified specification contains a written description of the invention, and of the manner and process of making and using it, in such full, clear, concise, and exact terms as to enable any person skilled in the art to which it pertains, or with which it is most nearly connected, to make and use the invention, and sets forth the best mode contemplated by me of carrying out the invention; and

THAT I acknowledge the duty to disclose to the U.S. Patent and Trademark Office all information known to me to be material to patentability as defined in Title 37, Code of Federal Regulations, §1.56.

1009236-050602

I HEREBY CLAIM foreign priority benefits under Title 35, United States Code § 119(a)-(d) or § 365(b) of any foreign application(s) for patent or inventor's certificate, or § 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below any foreign application for patent or inventor's certificate or of any PCT international application having a filing date before that of the application on which priority is claimed.

Prior Foreign Application Number	Country	Foreign Filing Date	Priority Claimed?	Certified Copy Attached?

I HEREBY CLAIM the benefit under Title 35, United States Code § 119(e) of any United States provisional application(s) listed below.

U.S. Provisional Application Number	Filing Date
60/137,860	June 7, 1999

I HEREBY CLAIM the benefit under Title 35, United States Code, § 120 of any United States application(s), or § 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application in the manner provided by the first paragraph of Title 35, United States Code, § 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

U.S. Parent Application Number	PCT Parent Application Number	Parent Filing Date	Parent Patent Number

I HEREBY APPOINT the following registered attorneys and agents of the law firm of FOLEY & LARDNER:

SCOTT D. ANDERSON	Reg. No. <u>46,521</u>
RUSSELL J. BARRON	Reg. No. <u>29,512</u>
DAVID J. BATES	Reg. No. <u>39,902</u>
STEVEN C. BECKER	Reg. No. <u>42,308</u>
EDWARD W. BROWN	Reg. No. <u>22,022</u>
CHARLES G. CARTER	Reg. No. <u>35,093</u>
ALISTAIR K. CHAN	Reg. No. <u>44,603</u>
JOHN C. COOPER III	Reg. No. <u>26,416</u>

JEFFREY N. COSTAKOS	Reg. No. 34,144
WILLIAM J. DICK	Reg. No. <u>22,205</u>
BARRY L. GROSSMAN	Reg. No. <u>30,844</u>
JEFFREY S. GUNDERSEN	Reg. No. <u>47,619</u>
PAUL S. HUNTER	Reg. No. <u>44,787</u>
JOHN M. LAZARUS	Reg. No. <u>48,367</u>
KENNETH G. LEMKE	Reg. No. <u>47,746</u>
KEITH D. LINDENBAUM	Reg. No. <u>40,365</u>
DAVID G. LUETTGEN	Reg. No. <u>39,282</u>
RICHARD J. MC KENNA	Reg. No. <u>35,610</u>
JAMES G. MORROW	Reg. No. <u>32,505</u>
JASON E. PAULS	Reg. No. <u>45,651</u>
TODD A. RATHE	Reg. No. <u>38,276</u>
MICHAEL D. RECHTIN	Reg. No. <u>30,128</u>
MARCUS W. SPROW	Reg. No. <u>48,580</u>
M. REED STAHELI	Reg. No. <u>47,859</u>
CHRISTOPHER M. TUROSKI	Reg. No. <u>44,456</u>
JOHN A. VANOPHEM	Reg. No. <u>38,646</u>
JAMES A. WILKE	Reg. No. <u>34,279</u>
JOSEPH N. ZIEBERT	Reg. No. <u>35,421</u>
WALTER E. ZIMMERMAN	Reg. No. <u>40,883</u>

to have full power to prosecute this application and any continuations, divisions, reissues, and reexaminations thereof, to receive the patent, and to transact all business in the United States Patent and Trademark Office connected therewith.

I request that all correspondence be directed to:

Steven C. Becker
FOLEY & LARDNER
Firstar Center
777 East Wisconsin Avenue
Milwaukee, Wisconsin 53202-5367

Telephone: (414) 297-5571
 Facsimile: (414) 297-4900

I UNDERSTAND AND AGREE THAT the foregoing attorneys and agents appointed by me to prosecute this application do not personally represent me or my legal interests, but instead represent the interests of the legal owner(s) of the invention described in this application.

I FURTHER DECLARE THAT all statements made herein of my own knowledge are true, and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

100 Name of first inventor

David BLAKER

Residence

Holland, MI 49423

Citizenship

U.S.A.

Post Office Address

~~240 East 19th Street~~ → 557 Bay Ave. (DB)
Holland, MI 49423

Inventor's signature

David A. Blaker

Date

April 16, 2002

200 Name of second inventor

Matthew CARDWELL

Residence

Holland, MI 49423

Citizenship

U.S.A.

Post Office Address

5356 144th Avenue
Holland, MI 49423

Inventor's signature

Matthew L. Cardwell

Date

April 9, 2002

Name of third inventor

Paul DUCKWORTH

Residence

Holland, MI 49424

Citizenship

U.S.A.

Post Office Address

224 159th Avenue
Holland, MI 49424

Inventor's signature

Date

400 Name of fourth inventor

Brian HONECK

Residence

Holland, MI 49424

Citizenship

U.S.A.

Post Office Address

13034 Blueberry Lane
Holland, MI 49424

Inventor's signature

Brian Honeck

Date

April 8, 2002

10009236.050602

300

Name of first inventor David BLAKER

Residence Holland, MI 49423

Citizenship U.S.A.

Post Office Address ~~240 East 19th Street~~ → 557 Bay Ave. (DB)
Holland, MI 49423

Inventor's signature David A. Blaker

Date April 16, 2002

Name of second inventor Matthew CARDWELL

Residence Holland, MI 49423

Citizenship U.S.A.

Post Office Address 5356 144th Avenue
Holland, MI 49423

Inventor's signature Matthew L. Cardwell

Date April 9, 2002

Name of third inventor Paul DUCKWORTH

Residence ~~Holland, MI 49424~~ → Elkhart, IN 46917 (PD)

Citizenship U.S.A. IN

Post Office Address ~~224 159th Avenue~~ → 29036 Hillary Lane (PD)
~~Holland, MI 49424~~ Elkhart, IN 46917 (PD)

Inventor's signature Paul C. Duckworth

Date April 19, 2002

Name of fourth inventor Brian HONECK

Residence Holland, MI 49424

Citizenship U.S.A.

Post Office Address 13034 Blueberry Lane
Holland, MI 49424

Inventor's signature Brian Honeck

Date April 8, 2002